



BC2 Automation Controller



The BitWise Controls BC2 has all the processing power of our BC1 controller, but in a mid-sized form factor. This controller is perfect for situations where you have fewer devices to control, but still need the highest level of performance

- A built-in astronomical clock provides event scheduling based on time of day, sunrise, and sunset
- Customizable email notifications
- Supports two-way interaction with serial and networked devices
- Communicates with every BitWise user interface and controller on your network
- On-board relays and signal sensing ports allow interaction with mechanical devices
- Can be rack or shelf mounted

| Connectivity | |
|-----------------------|---------------------------------|
| Ethernet | 10/100 |
| USB 2.0 | 2 Ports - Future Expansion |
| Device Control | |
| IR Ports | 4 (routable, attenuable) |
| RS232 | 2 (1 DB9, 1 Terminal Strip) |
| Relays | 2 (DPST) |
| Signal Sense | 2 (Analog or Digital) |
| Network Devices | Yes |
| Dimensions | |
| H x W x D | 1 11/16" x 7 9/16" x 4 7/8" |
| H x W x D (packaging) | 4" x 12" x 9" |
| Mounting | |
| Shelf | Yes |
| Rack | Yes (rack ears sold separately) |
| Power | |
| External | 12VDC - 0.5A (adapter included) |