



MX-60M

TABLETOP MODEL MIXER AMPLIFIER

Compact mixer amplifier provided with built-in source, for use in numerous commercial and industrial applications. Provided with individual volume control for each input channel and protection against short-circuits and thermal overload.



Listening to pleasant background music and creating the right atmosphere in this shop: nothing could be easier thanks to the budget-friendly MX-60M!

output capacity	100V
output capacity RMS	8Ω
frequency range	80 Hz - 18 kHz < 0,5% THD
zones	1
direct output	4-8 Ohm / 70V / 100V
tone control	yes
built-in source	USB/SD
	FM tuner
	Bluetooth
line-out	yes (built-in source, channel 2/3)
MIC input	3 (1 XLR/ 2 jack 6,3 mm)
AUX input	2 RCA
priority input	1 (phoenix + contact)
priority levels	3
power supply	240V AC
power consumption	210W
dimentions (h x w x d)	76 x 270 x 230mm
weight	3,59 kg

